
DATA SHEET Liquid Level Switch

Optomax Digital LLC510D3



Optomax Digital liquid level switches are ideal for applications with restricted space that require a miniature, low power and low cost sensing solution.

The microcontroller based sensor is solid state, incorporating an infra-red LED and phototransistor which are optically coupled by the tip when the sensor is in air. When the sensing tip is immersed in liquid, the infra-red light escapes making the output change state.



Housing/ **Mounting**



Output Type / Logic





100mA

 $4.5V_{DC}$ to $15.4V_{DC}$

2.5mA max. (Vs = 15.4V_{DC})



Supply Voltage



Output Current



Temp







Supply voltage (Vs)

Supply current (Is) Output sink and source

current (lout)

Standard: -25°C to +80°C Operating temperatures Extended: -40°C to +125°C

Standard: -30°C to +85°C Storage temperatures Extended: -40°C to +125°C

Trogamid® or Polysulfone1 Housing material

Sensor termination 24AWG. 250mm PTFE wires, 8mm tinned

M10x1³ Mounting thread² 20bar 4 Operating pressure

Tightening torque 1.5Nm / 13.26 in-lb maximum

OUTPUT VALUES

Output Voltage⁵ (Vout):

lout = 100mAOutput High Vout = Vs - 1V max **Output Low**

Vout = 0V + 0.5V max



- Before use check that the fluid in which you wish to use these devices is compatible with Polysulfone.
- 2) Sensor is mounted from inside vessel.
- 3) Hex nut and O-ring sold separately.
- 4) When correctly sealed.
- Voltages applicable to output value stated.

Apollosense Ltd

Adress: Room 712, Huaneng Building, Shennan Zhong Road, Shenzhen 518031,

Tel: (86-755) 83680810 83680820 83680830 83680860 Fax: (86-755) 83680866

Hong Kong:

Adress: Unit 1502, Hollywood Plaza, 610 Nathan Road, Mong Kok, Kln., H.K.

Tel: (852) 2737 0903 Fax: (852) 2737 0938 Email: sales@apollounion.com

Apollosense








All dimensions shown in mm. Tolerances = ±1mm.

Sensor mounted from inside vessel

LLx5x0 Series








Wire	Designation
Red	Vs
Green	Output
Blue	0V

CIRCUIT DIAGRAM

Digital Output High in Air




CAUTION: Take care when connecting loads.

The minimum load impedance should not exceed Vs/max output current.

NOTE: Shorting the output to Vs or 0V will result in irreparable damage to the sensor.

ORDER INFORMATION

Specify the part number listed below when ordering.



OCAUTION

Do not exceed maximum ratings and ensure sensor(s) are operated in accordance with their requirements.

Carefully follow all wiring instructions. Incorrect wiring can cause permanent damage to the device.

Apollo Sensing Ltd recommend using alcohol based cleaning agents. Do NOT use chlorinated solvents such as tricholerthane as these are likely to attack the sensor material.

Failure to comply with these instructions may result in product damage.

INFORMATION

As customer applications are outside of Apollosense Ltd.'s control, the information provided is given without legal responsibility.

Customers should test under their own conditions to ensure that the equipment is suitable for their intended application. Before use, check that the fluid in which you wish to use these devices is compatible with Polysulfone.

General Note: Apollo Sensing Ltd. reserves the right to make changes to product specifications without notice or liability. All information is subject to Apollo Sensing Ltd.'s own data and considered accurate at time of going to print.



Apollosense Ltd

Shenzhen:

Adress: Room 712, Huaneng Building, Shennan Zhong Road, Shenzhen 518031,

China

Tel: (86-755) 83680810 83680820 83680830 83680860 Fax: (86-755) 83680866 Hong Kong:

Adress: Unit 1502, Hollywood Plaza, 610 Nathan Road, Mong Kok, Kln., H.K.

Tel: (852) 2737 0903

Fax: (852) 2737 0938

Email: sales@apollounion.com